

Multi Charging Dock

7 Port USB Charging Station



User Manual

Thank you for purchasing the Satechi Multi Charging Dock! With 3 2.4A ports plus 4 1A ports, you can easily charge 3 tablets and 4 smart phones at the same time. Included with the Multi Charging Dock is a 64.98W, 19V/3.42A power supply.

With the Multi Charging Dock, you can easily bring order and power to your favorite 7 mobile devices. Each dock is fashioned with anti-scratch silicone rubber, so your devices won't have any risk of damage. When you need to pause charging, simply use the on/off switch. The ventilation system on the bottom of the dock prevents overheating.

Features:

Charge 7 devices on a single outlet.

2.4Amp x 3 ports and 1Amp x 4 ports

One on/off main power button

Power Supply: 64.98W adapter 19V/3.42A

Scratch free design

Surge protection on each port

Product dimension: **7.4 x 5.5 x 2.6 in**

Specification :

Specification	
Power Supply	DC: 19V 3.42A
USB output current	4.75~5.25V

USB current supply	3x2.4A+4x1A
Current of standby mode	<50mA, Working efficiency >85%

Product using environment

Working temperature	0~40C	Storage temperature	-20~85C
Working Humidity	5% (0C) ~90% (40C)	Storage Humidity	5%~95%

Product Package

- ◆ Charging station *1
- ◆ Power supply*1
- ◆ User manual

2.4A:

Input Voltage	Output port	Output Voltage	Output Current	Output Current
DC 19V/3.42A	5-7	5V	2.4A	For iPad, tablets etc.

1A:

Input Voltage	Port No.	Output Voltage	Output Current	Fit for
DC 19V/3.42V	1-4	5V	1A	For iPad, iPhone, Samsung, tablet and other smart phones etc.